

Super Reverb BOM

Part Type	Quantity	Part #	Description
Cabinet	1	4000113	Super Reverb Style Cabinet
Chassis	1	5151040	Super Reverb Style Chassis
	1	5151111	Large Cap Pan
Faceplates	1	9131551	Faceplate for SR - no logo
	1	9131321	Backplate for DR/SR
Fiberboard	1	7126042	AB763 Fiberboard
	1	7126045	Large Cap Board
	1	7126050	Diode Board - Tube Rect
	1	7126080	Speaker wiring harness board
Tubes	2	2000006	Matched JJ616 (alt Svet)
	4	2000000	JJ12ax7/ECC83 (alt Sov WA/B)
	2	2000001	JJ12at7/ECC81 (alt EH)
	1	2000010	JJ GZ34/5AR4 (alt Ch)
Speakers	4	4014100	C10Q
Plug	1	2195120	Flat Right Angle Plug
Speaker Wire	3	Z4132118	Black 18 Ga
	3	Z4132218	White 18 Ga
Reverb Parts	1	4042100	Mojotone Black Tolex Reverb Tank Bag (Large)
	1	4037200	Reverb Tank - 4AB3C1B (Fender, Marshall, Ampeg 2-Spr
	1	4043200	Mojotone Vintage Reverb Wire Kit
Transformers	1	MOJO762	Super Reverb Style Power
	1	MOJO774	Super Reverb Style Output
	1	MOJO777	6L6 Choke
	1	MOJO776	Rever Driver Transformer
Switches	1	4051000	Fender Style 2 button black footswitch
	2	4111402	110-63
	1	4114100	112-63
	2	4110400	Bright Switch
Jacks	5	2195112	Switchcraft 12A (alt Mojo)
	1	2195111	Switchcraft 11 alt Mojo)
	4	1100565	Mojo Panel Mount RCA inputs
Pilot Light	1	2281001	Pilot light assy
	1	9990052	Red Jewel
	1	Z8280300	#47 Bulb
Sockets	6	4070220	Grey 9 pin socket with shield mount
	3	4050001	Octal Socket
Potentiometers	2	9026000	CGE 1 Meg A
	4	9024000	CGE 250K A
	1	9023001	CGE 100K L
	1	9027000	CGE 3M RA
	1	4922000	CGE 50K RA
	1	9021000	CGE 10K A
	1	9021001	CTS 10K Linear bias pot
Knobs	10	7230001	Mojo Black Chickenhead Knob
Power Cord	1	7143718	10' power cord 18/3 - (alt 6' or removable)
Optoisolator	1	4113400	Optoisolator
Fuseholder	1	4210100	New Style little fuse fuseholder
Fuse	1	4197002	2A 3AG fuse
Strain Relief	6	7237021	3/8" Grommet

Super Reverb BOM

	1	7236001	Strain Relief for 18/3
Hardware	20	Z392PZ02	4-40 1/4" Pan Head Zinc (alt black)
	20	Z362KSZ0	4-40 Keps Nuts
	8	Z393PB04	6-32 x 1/2 Pan Head BO (alt zinc)
	8	Z2250414	6-32 Keps Nuts
	8	Z394PB04	8-32 x 1/4" Pan Head BO (alt zinc)
	8	Z2253402	8-32 Keps Nuts
	8	Z395PB03	10-32 x 3/4" Pan Head BO (alt zinc)
	8	Z365KSZ0	10-32 Keps Nuts
	1	2305001	Large chassis straps (w hardware)
	1	5125013	3 lug terminal strip
Wire	30	Z4132322	Mojo yellow 22 ga CC wire
	10	Z4132518	Green Filament Wire
Diodes	1	3000002	Diode - 1N4007 Rectifier DO-41 1A 1000v
Capacitors	7	5163255	25/50 Sprague
	1	5163100	100/100 Sprague
	3	5163205	20/500 Sprague
	2	5163103	100/350 Sprague
	1	5165001	.001/600 Orange Drop
	1	5165003	.003/600 Orange Drop
	3	5165022	.022/600 Orange Drop
	2	5165047	.047/600 Orange Drop
	6	5165100	.1/600 Orange Drop
	2	5167010	.01/500 Ceramic Disc
	1	5167020	.02/500 Ceramic Disc
	1	5167030	10pf/500 Ceramic Disc
	1	5164500	500pf/500 mica
	2	5164250	250pf/500 mica
	2	5164120	120pf/500 mica
Resistors	1	Z7291500	1k 2 Watt Metal
	1	Z7291502	4.7k 2 Watt Metal
	2	Z7291506	220k 2 Watt Metal
	3	7292451	470 Ohm 1 Watt CC
	3	7294101	100ohm 1/2 watt CC
	1	7294471	470ohm 1/2 watt CC
	3	7294821	820ohm 1/2 watt CC
	4	7294152	1.5k 1/2 watt CC
	1	7294222	2.2k 1/2 watt CC
	1	7294272	2.7k 1/2 watt CC
	1	7294682	6.8k 1/2 watt CC
	1	7294223	22k 1/2 watt CC
	1	7294273	27k 1/2 watt CC
	4	7294683	68k 1/2 watt CC
	1	7294823	82k 1/2 watt CC
	12	7294104	100k 1/2 watt CC
	7	7294224	220k 1/2 watt CC
	1	7294274	470k 1/2 watt CC
	7	7294105	1m 1/2 watt CC
	1	7294225	2.2m 1/2 watt CC
	1	7294335	3.3m 1/2 watt CC

Super Reverb BOM

	1	7294106	10m 1/2 watt CC
Some of the parts contained in this kit are subject to availability. Mojo Musical Supply reserves the right to change or substitute any and all of the parts contained in this amplifier kit without advertisement or notification to the buyer. Part substitutions made by Mojo Musical Supply are guaranteed not to effect the integrity or operation of your amplifier kit.			